













Individual chargers

| model | power supply | | connections | sketch | charge |
|----------|--------------|--------|---|---|--------|
| C-64P | 230 | V.a.c. | Cable with European plug |  | slow |
| C-64U | 85 ÷ 265 | V.a.c. | Cable with European plug |  | slow |
| C-COR | 230 | V.a.c. | Detachable cable with European plug |  | slow |
| | 12 | V.d.c. | Detachable cable with cigarette-lighter adaptor |  | |
| C-6412P | 12 | V.d.c. | Cable with flying lead |  | slow |
| C-6424P | 24 | V.d.c. | Cable with flying lead |  | slow |
| C-6472P | 60 ÷ 370 | V.d.c. | Cable with flying lead |  | slow |
| C-64PQ | 85 ÷ 265 | V.a.c. | Cable with European plug |  | fast |
| C-CORQ | 85 ÷ 265 | V.a.c. | Detachable cable with European plug |  | fast |
| | 12 | V.d.c. | Detachable cable with cigarette-lighter adaptor |  | |
| C-6424PQ | 12 and 24 | V.d.c. | Cable with flying lead |  | fast |
| C-6472PQ | 60 ÷ 370 | V.d.c. | Cable with flying lead |  | fast |

Multiple chargers

| model | power supply | | connections | sketch | charge |
|-----------|--------------|--------|--------------------------|---|--------|
| CM5-C64P | 230 | V.a.c. | Cable with European plug |  | slow |
| CM5-C64PQ | 85 ÷ 265 | V.a.c. | Cable with European plug | | fast |

To request mechanical fastening, both for individual and multiple chargers, add "E" to the reference. Example:

C-64UE

└─ Mechanical fastening

◇ The usage temperature of the chargers ranges from -10°C to 40°C. Out of it, the correct charge of the torches cannot be guaranteed.

◇ Watertight versions of some chargers are available.

◇ Different types of plugs can be supplied.

Shoulder strap

Ref. CHR-1



Fixed mounting in vehicle or on wall (both on a horizontal and vertical surface): the charger has two wings with holes for anchoring with screws.

In order to achieve a totally immobile installation, it is necessary that the charger incorporates the mechanical fastening option.



Standard multiple charger with mechanical fastening



C-64 Series

Chargers compatible with QR, LR, HR, LRX and HRX torches series, capable to optimally charge different types of batteries. The charger receives the torch and charges its battery by means of two flying contact leads that supply a constant current without electrical hazard. Individual or multiple chargers (for 5 torches).



Standard individual charger



Standard individual charger with mechanical fastening

Led indicator in torch

The charging status of the battery of the torch is indicated through a led indicator.

The torch must be left on the charger to keep it completely charged for an indefinite time with no harm to its battery.



- 0% ÷ 20%
- 20% ÷ 60%
- 60% ÷ 100%
- > 100%

Led indicator in charger

The charger also incorporates a led indicator, whose function is to indicate the correct connection of the charger to the mains and the charging process of the torch, when it is placed on it.



- Slow charger**
- Connected to the mains
 - Torch charging (slow) & maintenance charge
- Fast charger**
- Connected to the mains
 - Torch charging (fast)
 - Maintenance charge

Charging times

| battery | slow (h) | fast (h) |
|---------------------------|----------|----------|
| 1.6 or 2 Ah Ni-Cd / Ni-MH | 36 | 5 |
| 4 Ah Ni-Cd / Ni-MH | 36 | 8 |
| 2.6 Ah Li-Ion | 24 | 5 |
| 5.2 Ah Li-Ion | 48 | 9 |

Dimensions

